


Motion detectors 1.1 m



Motion detector 1.1 m

Operating voltage	230 V~
Frequency	50/60 Hz
Motor switching current at $\cos\phi = 0.6$	max. 1 A
Power consumption (standby)	< 300 mW
dimmable 230 V LED lamps	8 ... 40 W
230 V incandescent lamps and halogen lamps	25 ... 200 W
Dimmable conventional transformers	25 ... 150 VA
dimmable electronic transformers and bi-mode transformers	25 ... 150 W
Compact fluorescent lamps	12 ... 48 W
Nominal mounting height	1.1 m
Response sensitivity, settable	$\approx 10 \dots 100 \%$
Response brightness, adjustable	$\approx 5 \dots 1000 \text{ lx}, \infty \text{ lx (day)}$
Detection angle	180°
Detection field, semi-oval shaped	$\approx 10 \times 12 \text{ m}$
Delay time	$\approx 3 \text{ min}$
Lockout time	2 s
Operating temperature	$-5 \dots +45^\circ\text{C}$
Screw terminals (max.)	$2 \times 1,5 \dots 2,5 \text{ mm}^2$
Insertion depth	32 mm


- with switch-off pre-warning (can be deactivated)
- with 2 potentiometers for fine adjustment of response brightness and sensitivity
- with red status LED
- with button for on/off/automatic
- short-circuit and overload proof (electronic fuse)
- overheating protection (display using LEDs)

SUITABLE FOR	ORDER NO.	PAGE
Cover for motion detector compact 1.1m 1190 ..		2

Switches on for the duration of the delay time when the minimum response brightness level is infringed and if people are detected.
Only suitable for indoor areas!



DESIGN	ORDER NO.	PU
Motion detector 1.1 m	★ 2995	1



Motion detector with neutral conductor connection 1.1m

Operating voltage	230 V~
Frequency	50/60 Hz
Motor switching current at $\cos\phi = 0.6$	max. 1 A
Power consumption (standby)	< 350 mW
230 V LED lamps	max. 350 W
230 V incandescent lamps and halogen lamps	max. 1000 W
Conventional transformers	max. 1000 VA
Electronic transformers and dual-mode transformers	max. 1000 W
Fluorescent lamps	max. 200 VA
Compact fluorescent lamps	max. 350 W
Nominal mounting height	1.1 m
Response sensitivity, settable	$\approx 10 \dots 100 \%$
Response brightness, adjustable	$\approx 5 \dots 1000 \text{ lx}, \infty \text{ lx (day)}$
Detection angle	180°
Detection field, semi-oval shaped	$\approx 10 \times 12 \text{ m}$
Delay time	$\approx 3 \text{ min}$
Lockout time	2 s
Operating temperature	$-5 \dots +45^\circ\text{C}$
Screw terminals (max.)	$2 \times 1,5 \dots 2,5 \text{ mm}^2$
Insertion depth	32 mm

- with switch-off pre-warning (can be deactivated)
- with 2 potentiometers for fine adjustment of response brightness and sensitivity
- with red status LED
- with button for on/off/automatic
- short-circuit and overload proof (electronic fuse)
- overheating protection (display using LEDs)

SUITABLE FOR	ORDER NO.	PAGE
Cover for motion detector compact 1.1m 1190 ..		2

Switches on for the duration of the delay time when the minimum response brightness level is infringed and if people are detected.
Only suitable for indoor areas!



DESIGN	ORDER NO.	PU
Motion detector with neutral conductor connection 1.1m	★ 2996	1

Motion detectors

Motion detectors 1.1 m



Cover for motion detector compact 1.1m

■ with fixing element

SUITABLE FOR	ORDER NO.	PAGE
Motion detector 1.1 m	2995	1
Motion detector with neutral conductor connection 1.1m	2996	1

DESIGN	ORDER NO.	PU
Berker S.1/B.3/B.7		
white glossy	★ 1190 89 82	10
polar white glossy	★ 1190 89 89	10
polar white matt	★ 1190 19 09	10
anthracite matt	★ 1190 16 06	10
aluminium matt, lacquered	★ 1190 14 04	10

